

Reg. No. :

| | | | | | | | | | |
|--|--|--|--|--|--|--|--|--|--|
| | | | | | | | | | |
|--|--|--|--|--|--|--|--|--|--|

Question Paper Code: 46403

B.E. / B.Tech. DEGREE EXAMINATION, NOV 2018

Sixth Semester

Electronics and Communication Engineering

14UEC603 - ANTENNA AND WAVE PROPAGATION

(Regulation 2014)

Duration: Three hours

Maximum: 100 Marks

Answer ALL Questions

PART A - (10 x 1 = 10 Marks)

- How do the elements of an active region behave?
(a) Inductive (b) Capacitive (c) Resistive (d) None of the above
- Consider a lossless antenna with a directive gain of +6 dB. If 1 mW of power is fed to it, the load power radiated by the antenna will be
(a) 4mW (b) 1mW (c) 7mW (d) 1/4mW
- At which angles does the front to back ratio specify an antenna gain?
(a) 0° & 180° (b) 90° & 180° (c) 180° & 270° (d) 180° & 360°
- The array that does not produce side lobes excepting principal lobe is
(a) Broad side array (b) End fire array
(c) Yagi-Uda array (d) Binomial array
- Corrugations in conical horn antenna is provided to improve
(a) Directivity (b) Impedance matching
(c) Beam symmetry (d) Bandwidth

6. The relation between slot and dipole impedances is
- (a) $Z_s Z_d = Z_i^2/4$ (b) $Z_s Z_d = Z_i^2/2$
(c) $Z_s Z_d = Z_d^2/4$ (d) $Z_s Z_d = Z_d^2/2$
7. A 13 element Yagi-uda antenna array produces a maximum gain of _____ dB (approx.).
- (a) 5 (b) 9 (c) 14 (d) 3
8. For a Hertz dipole antenna, the Half Power Beam Width (HPBW) in the E-Plane is
- (a) 360° (b) 180° (c) 90° (d) 45°
9. If the maximum electron density for F-layer in ionosphere is 4×10^6 electrons/cm³, then what will be the critical frequency of EM wave for F-layer?
- (a) 4 MHz (b) 9 MHz (c) 18 MHz (d) 25 MHz
10. _____ is not a type of fading.
- (a) Polarization (b) Skip (c) Interference (d) None of these

PART - B (5 x 2 = 10 Marks)

11. Distinguish far field and near field region of an antenna.
12. List out the advantages and disadvantages of loop antenna.
13. Define a Hertzian dipole.
14. Mention the relation between the length 'l' and spacing 'S' of adjacent elements of log periodic dipole array.
15. What are the types of Ground waves?

PART - C (5 x 16 = 80 Marks)

16. (a) Discuss in detail on different apertures of an antenna and explain the relation between them (16)

Or

- (b) (i) In a microwave link, two identical antennas operating at 10GHz are used with power gain of 40db. If the transmitted power is 1 watt, find the received power if the range of the link is 30km. (8)

(ii) A thin dipole antenna is $\lambda/2$, if it's $R_L = 1.5\Omega$ find R_r and its efficiency. (8)

17. (a) Derive the fields radiated from a half wave dipole antenna. Also find the power radiated from the same. (16)

Or

(b) Elucidate linear array of 4 isotropic elements spaced $\lambda/2$ apart and with equal currents fed out phase, plot the radiation pattern in polar coordinates. (16)

18. (a) Design a rectangular micro strip patch with dimensions W and L over a single substrate, whose center frequency is 10 GHz. The dielectric constant of the substrates is 10.2 and the height of the substrate is 0.127 cm. Determine the physical dimensions W and L of the patch taking into account fringing fields. (16)

Or

(b) Express the importance of Babinet's principle on complementary antennas in detail. (16)

19. (a) Explain the radiation mechanism of a 2 element Yagi-Uda Antenna. Derive its gain expression. (16)

Or

(b) (i) Design a log periodic dipole array with 7 db gain and a 4 to 1 bandwidth. Given from "Carrel" curve that 7 db gain corresponds to $\alpha=15^\circ$, $K=1.2$ and $S/\lambda=0.15$. (8)

(ii) Elaborate Gain and Directivity measurements in antenna. (8)

20. (a) Explain the various layers of Ionosphere (16)

Or

(b) At a 150 km height in the ionosphere, the electron density at night is about $2 \times 10^{12} \text{ m}^{-3}$ and the signal MUF is 1.5 times the critical frequency for a transmission distance of 600km. Compute the following: (i) Critical frequency (ii) Relative dielectric constant (iii) Phase constant (iv) Wave impedance (v) Wave velocity. (16)

