

Reg. No. :

--	--	--	--	--	--	--	--	--	--	--	--	--	--	--

**Question Paper Code:R3B03**

B.E./B.Tech. DEGREE EXAMINATION, NOV 2025

Third Semester

R21UBM303–PRINCIPLES OF SIGNALS AND SYSTEMS

Biomedical Engineering

(Regulations R2021)

Duration: Three hours

Maximum: 100 Marks

Answer ALL Questions

PART A - (10 x 2 = 20 Marks)

1. Is the signal  $x(t) = 10\cos(2\pi t) + \sin(5\pi t)$  a periodic signal. If it is, determine the fundamental period? **CO2-App**
2. Differentiate between causal and non-causal systems. **CO1 - U**
3. State the trigonometric form of the Fourier series representation of a periodic signal? **CO1 U**
4. State Convolution property for Laplace transforms. **CO1 U**
5. Define impulse response of a system. **CO1 U**
6. What are the tools used for analysis of LTI-CT systems? **CO1 U**
7. Write the main condition to avoid aliasing? **CO1 U**
8. Define Z transform. **CO1 U**
9. Write the convolution sum with its equation  $x_1(n)$  &  $x_2(n)$  as two input sequence. **CO1 U**
10. Is the discrete time system described by the difference equation  $y(n) = x(-n)$  causal? **CO3 App**



14. (a) (i) Consider an analog signal  $x(t) = 5\cos 200\pi t$ . CO3 -App (16)  
 (a) Examine the minimum sampling rate to avoid aliasing effect.  
 (b) If sampling rate  $F_s = 400\text{Hz}$ . Determine the Discrete time signal after sampling?  
 (ii) Explain types of sampling.
- Or
- (b) Infer the Z-transform and ROC of CO3-App (16)  
 $x[n] = 2^n u(n) + 3^n u(-n - 1)$ . Experiment the Z-transform of the sequences  
 $x(n) = \{5, 3, 2, 4, 0, 1, 6\}$ .
15. (a) i. Formulate the linear convolution of  $x(n) = \{1, 4, 3, 2\}$  and CO3-App (16)  
 $h(n) = \{1, 3, 2, 1\}$   
 ii. In LTI discrete time system  
 $y(n) = \frac{3}{2}y(n - 1) - \frac{1}{2}y(n - 2) + x(n) + x(n - 1)$  is given an input  
 $x(n) = u(n)$ . Observe the transfer function of the system.
- Or
- (b) Evaluate the impulse and step response of the system described CO3-App (16)  
 by the following difference equation  $y(n) + \frac{1}{3}y(n - 1) = x(n)$ .

