

Reg. No. :

--	--	--	--	--	--	--	--	--	--	--	--	--	--	--

Question Paper Code: R5D02

B.E./B.Tech. DEGREE EXAMINATION, NOV 2025

Fifth Semester

R21UCB502 COMPILER DESIGN

(Regulations R2021)

Duration: Three hours

Maximum: 100 Marks

Answer ALL Questions

PART A - (10 x 2 = 20 Marks)

1. Define patterns and lexemes with suitable example. CO1- U
2. $(ab/ab)^*$ Convert regular expression in to finite automata using Thompsons Construction. CO 6- App
3. Give short note on Grammar Types. CO 2- App
4. Define RDP. CO 2- Ana
5. Generate the intermediate representation of the statement .
A or B and not C. CO 6- Ana
6. How semantic Errors can be detected? CO 6- U
7. Define Basic Block and Flow Graph. CO 6- U
8. Give the application of DAGs. CO 6- U
9. Write the actions to perform the code generation algorithms. CO 2- U
10. Mention any two objectives of a good code generator. CO 2- U

PART – B (5 x 16= 80 Marks)

11. (a) (i) Explain the Role of Lexical Analyzer. CO1-U (8)
(ii) Write notes on specification of tokens. (8)
- Or
- (b) Explain various phases of compiler with neat sketch. CO1-U (16)

12. (a) Consider the following grammar CO2- App (16)

$E \rightarrow E + T \mid T$

$T \rightarrow TF \mid F$

$F \rightarrow F^* \mid a \mid b$

Construct the SLR parsing table for this grammar and also parse the input $a * b + a$

Or

(b) Check whether the following grammar is SLR (1) or not. Explain your answer with reasons. CO2- App (16)

$E \rightarrow E + E$

$E \rightarrow (E)$

$E \rightarrow E * E$

$E \rightarrow id$

13. (a) i) Draw the quadruple, triple and indirect triples for the following statement $a = b * - c + b * - c$. CO1-U (16)

(ii) Draw the quadruple, triple and indirect triples for the following statement $(a + b) * (c + d) - (a + b + c)$.

Or

(b) Translate the statement CO2-U (16)

$c = 0$

do {

 if ($a < b$) then

$x++$

 else

$x--$

$c++$

 } while ($c < 5$)

into three address statements.

ii) Convert the arithmetic expression $((A + B) * C) - (D / E)$ into postfix and prefix notations. Then, translate each notation into three-address code. Discuss the utility of postfix and prefix notations in compiler design.

14. (a) Describe the various types of peep-hole optimization techniques with examples CO1-U (16)

Or

(b) Explain the role of basic blocks and control flow graphs in data flow analysis. CO1-U (16)

15. (a) Explain the role of stack allocation in managing procedure calls and local variables. CO1-U (16)

Or

(b) Explain the basic structure and components of a simple code generator. CO1- U (16)

