

C

Reg. No. :

--	--	--	--	--	--	--	--	--	--	--

**Question Paper Code: 95B04**

B.E. / B.Tech. DEGREE EXAMINATION, MAY 2022

Fifth Semester

Biomedical Engineering

19UBM504 - PRINCIPLES OF DIGITAL SIGNAL PROCESSING

(Regulation 2019)

Duration: Three hours

Maximum: 100 Marks

Answer ALL Questions

PART A - (10x 2 = 20 Marks)

1. How many stages of decimations are required in the case of a 64 point CO1- App
2. Write the differences and similarities between DIT and DIF? CO1- U
3. What is the advantage of direct form II realization when compared to direct form I realization? CO2- U
4. Compare IIR and FIR filters CO2- U
5. Define Gibbs Phenomenon. CO3- U
6. List different methods of realization of LTI system CO3- U
7. Define finite word length effects CO5- U
8. Give the formula for variance of noise source due to rounding off CO5- U
9. Compare Von Neumann and Harvard architecture in DSP CO6- U
10. What is MFLOPS CO6- U

PART – C (5 x 16= 80 Marks)

11. (a) Evaluate radix 2 – DIT FFT algorithm and obtain DFT of the sequence  $x(n) = \{1,2,3,4,4,3,2,1\}$ . CO1- App (16)  
Or  
(b) Derive radix- 2 to DIF-FFT algorithm and Draw the butterfly diagram of each stage considering  $N=8$  CO1- U (16)

12. (a) (i) Design a low pass analog butterworth filter satisfying the following specifications  $\alpha_p = 0.1 \text{ dB}$   $\alpha_s = 44 \text{ dB}$   $\omega_p = 20 \text{ rad/sec}$  and  $\omega_s = 30 \text{ rad/sec}$  and  $\omega_{sf} = 100 \text{ rad/sec}$  CO2- App (8)

- (ii) Realize the given LTI system using Form II method  $y(n) = x(n) + 2x(n-1) + y(n-1)$  CO3- App (8)

Or

- (b) (i) Given the specifications  $\alpha_p = 3 \text{ dB}$   $\alpha_s = 16 \text{ dB}$   $f_1 = 1 \text{ KHz}$  and  $f_2 = 2 \text{ KHz}$ . Determine the order of the filter using Chebyshev approximation find  $H(s)$  CO2- App (8)

- (ii) Realize the given LTI system using parallel form  $H(z) = \frac{1+z^{-1}}{1+\frac{1}{8}z^{-1})(1+\frac{1}{2}z^{-1})}$  CO3- App (8)

13. (a) Design an ideal high pass filter with a frequency response  $H_d(e^{j\omega}) = 1$  for  $\frac{\pi}{4} \leq |\omega| \leq \pi$  CO4- Ana (16)

$$= 0 \text{ for } |\omega| \leq \frac{\pi}{4}$$

Find the values of  $h(n)$  for  $N = 11$  using hamming window. Find  $H(z)$  and determine the magnitude response.

Or

- (b) Determine the filter coefficients  $h_d(n)$  obtained by sampling  $H_d(e^{j\omega}) = e^{-j(N-1)\omega/2}$  for  $0 \leq |\omega| \leq \frac{\pi}{2}$  for  $N=7$  CO4- Ana (16)
- $= 0$  for  $\frac{\pi}{2} \leq |\omega| \leq \pi$

14. (a) (i) Discuss the different types of errors occurs due to truncation and rounding-off CO5- U (8)

- (ii) Draw the product quantization noise model of the system given below  $y(n) + 0.2y(n-1) + 0.5y(n-2) = x(n) + 2x(n-1)$  CO5- App (8)

Or

- (b) (i) With example discuss different types of number representation in Binary format CO5- U (8)
- (ii) For second order IIR filter  $H(z) = \frac{1}{(1-0.5z^{-1})(1-0.45z^{-1})}$ , study the effect of the shift in pole location with 3 bit coefficient representation in direct form and also comment on stability CO5- App (8)
15. (a) With neat diagram explain the functional blocks of TMS320C50 DSP CO6- U (16)
- Or
- (b) Discuss in detail the history of TMS processors and their applications CO6- U (16)

