

Reg. No. :

--	--	--	--	--	--	--	--	--	--

**Question Paper Code: 56424**

B.E. / B.Tech. DEGREE EXAMINATION, DEC 2021

Sixth Semester

Electrical and Electronics Engineering

01UEC624 - APPLIED DIGITAL SIGNAL PROCESSING

(Common to EIE and ICE)

(Regulation 2013)

Duration: Three hours

Maximum: 100 Marks

Answer ALL Questions

PART A - (10 x 2 = 20 Marks)

1. Compare deterministic and random signals.
2. Show that the discrete time system described by the input-output relationship  $y(n) = nx(n)$  is linear?
3. Summarize three methods of doing inverse Z-transform.
4. Deduce the convolution sum of two sequences of  $x(n) = \{3, 2, 1, 2\}$  and  $h(n) = \{1, 2, 1, 2\}$ .
5. Express the 2-point radix-2 DIT-FFT butterfly structure for DFT. What is its advantage?
6. Define twiddle factor of FFT.
7. Give the steps in the design of a digital filter from analog filter.
8. Distinguish between FIR filters and IIR filters.
9. Illustrate the block diagram of Modified Harvard architecture.
10. Mention various stages in pipelining.

PART - B (5 x 16 = 80 Marks)

11. (a) Explain the process of reconstruction of the signal from its samples with expression.

(16)

Or

- (b) State and prove the sampling theorem for strictly band limited signals of finite energy. (16)
12. (a) Discover the general solution of the difference equation  $y(n) = x(n) - 3y(n - 1)$  with initial condition  $y(-1) = 0$  and input  $x(n) = n^2 + n$ . (16)

Or

- (b) Determine the output sequence  $y(n)$  if  $x(n) = \{1, 2, 3, 2\}$  and  $h(n) = \{1, 2, 2\}$  using linear convolution graphical method. (16)
13. (a) Compute the eight-point DFT of the sequence  $x(n) = \{n + 1\}$ , Using the radix-2 decimation-in-time algorithm. (16)

Or

- (b) Calculate the DFT of the following sequence  $x(n)$  using the DIT-FFT algorithm.  $x(n) = \{0, 0, 0, 0, 1, 1, 1, -1\}$ . (16)
14. (a) Design a low pass filter using rectangular window by taking 9 samples of  $W(n)$  and with a cutoff frequency of  $1.2 \text{ rad/sec}$ . (16)

Or

- (b) Design an ideal low pass filter with a frequency response

$$H_d(e^{j\omega}) = \begin{cases} e^{-j3\omega}, & -\frac{\pi}{4} \leq \omega \leq \frac{\pi}{4} \\ 0, & \frac{\pi}{4} < |\omega| \leq \pi \end{cases}$$

Find the values of  $h(n)$  using hanning window and determine the transfer function  $H(z)$ . (16)

15. (a) Explain the architecture of TMS320C50 with a neat diagram. (16)

Or

- (b) (i) Explain assembly language instructions with suitable examples. (8)

(ii) Write a simple assembly language program and discuss the complete operation step by step. (8)